

**TENTATIVE**
**Case Outline :** 15 pins (See attached case outline drawing.)

**Function :** Current amp

**Use :** Video projectors

**Feature :** 2 channels/1 package for convergence use

Absolute Maximum Ratings at $T_a = 25^\circ\text{C}$				unit
Maximum Supply Voltage	$V_{CC}$	Note 1	$\pm 38$	V
Maximum Collector Current	$I_c$	Tr6,13 DC 1sec	+2.0	A
		Tr7,14 DC 1sec	-2.0	A
Thermal Resistance	$\theta_{j-c}$	Tr6,7,13,14 (Per power Tr)	3.0	$^\circ\text{C/W}$
Junction Temperature	$T_j$		150	$^\circ\text{C}$
Operating Case Temperature	$T_c$		105	$^\circ\text{C}$
Storage Temperature	$T_{stg}$		-30 to +105	$^\circ\text{C}$

Note 1. If the supply voltage is not balanced between  $+V_{CC}$  and  $-V_{CC}$ , the maximum rating of  $+V_{CC} - (-V_{CC})$  must be 76V. Further,  $|\pm V_{CC} \text{ max}| < 42.5\text{V}$  must be met.

**Operating Characteristics at  $T_a = 25^\circ\text{C}, R_g = 50\Omega$ , See attached Test Circuit.**

			min	typ	max	unit
Output Noise Voltage	$V_{NO}$	$V_{CC} = \pm 24\text{V}$				0.2 mVrms
Quiescent Current	$I_{cco}$	$V_{CC} = \pm 24\text{V}$		15	25	mA
Midpoint Voltage	$V_N$	$V_{CC} = \pm 24\text{V}$	-50	0	+50	mV
Output Delay Time	$t_D$	$V_{CC} = \pm 20.5\text{V}, f = 15.75\text{kHz}$ , triangular wave input $V_{P-P} = 1.5\text{V}$				1 $\mu\text{sec}$

**Remarks**

- For power supply at the time of test, use a constant-voltage power supply unless otherwise specified.
- The output noise voltage is represented by the peak value on rms scale (VTVM) of average value indicating type.

The application circuit diagrams and circuit constants herein are included as an example and provide no guarantee for designing equipment to be mass-produced. The information herein is believed to be accurate and reliable. However, no responsibility is assumed by SANYO for its use, nor for any infringements of patents or other rights of third parties which may result from its use.


Specifications and information herein are subject to change without notice.

**SANYO Electric Co., Ltd. Semiconductor Overseas Marketing Div.**  
 Natsume Bldg., 18-6, 2-chome, Yushima, Bunkyo-ku, TOKYO 113 JAPAN.


7039YT, TS STK4274-1/8

# STK4274


## Internal Equivalent Circuit (STK4274)



## Test Circuit (STK4274)




Case Outline (unit : mm)



Sample Application Circuit (STK4274)

Video projector convergence correction circuit  
 fH = 15.75kHz  
 Sample application to power supply selector



Design notes

1. Avoid pin-to-pin short, otherwise the IC will break down.
2. For mark ※, the constant is specified (tolerance ±10%). If you want to change the constant, consult us.